

5 / PRTS

Description

PERMANENT MAGNET ELECTRIC MACHINE WITH ENERGY SAVING CONTROL

Ins.
a1

Technical Field

The present invention relates to an energy generator as a dynamo-electric machine with separate employment of the interacting forces and their balancing with permanent magnets.

The term "dynamo-electric machine" designates any machine which converts mechanical energy into electrical energy and vice versa. The type of machine whereto the present invention refers is the one wherein a primary comprises a multiplicity of polar expansions and a secondary comprises a succession of heteronomous alternated permanent magnets.

Background Art

It is well known that both in motors and in generators of this kind, electromagnets act by attraction or repulsion over the entire pitch of the magnets in two semi-cycles, that is to say at full cycles from permanent magnet to permanent magnet, and hence in none of the known motors or generators is the active effect of the interaction of the magnets with the highly permeable ferromagnetic cores taken into account, nor is the equilibrium i.e. the balancing of the ferromagnetic forces which cancel out the permanent magnetic resistant torque to pass from one permanent magnet to the other.

Disclosure of Invention

Although in the considerations that follow reference shall be made, for the sake of convenience, mostly to motors, the same considerations apply for generators as well.

In particular, the invention constituting the subject of the invention is aimed at

determining at relative disposition between the pairs of electromagnets of the primary and the permanent magnets of the secondary which is able to harmonise the forces at play, whose magnetic nature is respectively permanent, ferromagnetic and electromagnetic.

5 Another aim of the present invention is to reach a high efficiency in the transformation of electrical into mechanical energy and vice versa thanks to an appropriate electrical power supply of the electromagnets of the primary in their interaction with the permanent magnets of the secondary.

Yet another aim of the present invention is to provide an electric motor which can be controlled by an appropriate control system according to the characteristics required in each particular case, with adequate sensors such as optical, magnetic, resistive, inductive or other types of transducers which, through electronic circuits with transistors, thyristors, or triac, drive the supply of power to the machine, as well as common brush collectors, able to provide current at alternating polar steps to the coils offset by a polar step, first one than the other in succession for four steps of complete cycle.

10 The invention, as it is characterised by the claims that follow, solves the problem of providing a dynamo-electric machine with the harmonisation of the interacting forces, of the type having a primary comprising one or more pairs of polar expansion positioned one at the centre of the permanent magnets and the others astride two
20 permanent magnets, mutually distanced by a polar step and each provided with a ferromagnetic core and with at least one electromagnetic coil, and a secondary comprising a succession of alternate heteronomous permanent magnets, and a related control system, which from a general point of view, is characterised in that each polar
25 step of electrical conduction spans half permanent magnet of said alternate heteronomous permanent magnets and in that said electrical conduction is driven at alternate phases: in the first step the coil or coils in negative feedback facing the centre of the permanent magnet, then in the second step the coil or coils in negative feedback which were astride the permanent magnets and which are in turn taken to

the centre, then the third step again the coil or coils in negative feedback of the first step but with opposite electrical polarity still in negative feedback, then the fourth step again the coil or coils in negative feedback of the second step with opposite electrical polarity still in negative feedback closing a complete electrical conduction cycle, the two phases are carried out for separate two fourths by a first coil of the balancing pair and for other separate two fourths by a second coil of the balancing pair offset by a polar step and always with electrical polarity suitable to obtain the negative feedback with the opposed permanent magnets and always at the output of each half alternate heteronomous permanent magnet. The invention lets the "natural" permanent magnetic force active in attraction of the alternate heteronomous permanent magnets with the high-permeability ferromagnetic cores be always unbalanced in attraction, first a ferromagnetic core than the other concurring to create a complete parallel and superposed dual cycle of "natural" mechanical energy which goes to the axis of the dynamo-electric machine together with the cycle of "artificial" electromagnetic energy transformed by negative feedback with the consequent addition of the two separate and parallel energies, obtaining a high efficiency of the machine of the invention.

Although in the present description the invention is described with reference to a rotatory dynamo-electric machine, it can also be applied to linear machines or annular linear machines and to devices for partial servo-controls.

Further features and advantages of the present invention shall become more readily apparent from the detailed description that follows, of preferred embodiments illustrated purely by way of non-limiting indication in the accompanying drawings.

Description of the Drawings

- Figure 1 schematically shows in cross section view an embodiment of a dynamo-electric machine according to the present invention;
- Figure 2 shows the basic components of the dynamo-electric machine of Figure 1 and a related diagram of the forces interacting between them;

- Figure 3 schematically shows a complete attraction and repulsion cycle between the basic components of the dynamo-electric machine of Figure 1;
- Figure 4 schematically shows a complete cycle of attraction and repulsion between pairs of electromagnets and magnets;
- Figure 5 shows a diagram of the electromagnetic energies at play in the cycle of Figure 4;
- Figure 6 shows a diagram of the ferromagnetic at play in the cycle of Figure 4;
- Figures 7 through 9 schematically show, in section view, respective different dispositions between primary electromagnets and secondary permanent magnets whereto the present invention can be applied.

Description of the Illustrative Embodiment

According to the present invention, Figure 1 schematically shows in cross section view an embodiment of an electric motor, taken for instance from an energy generator as dynamo-electric machine according to the present invention.

As shown in Figure 1, on a support base 1 is mounted a stator 2, the primary of the machine, coaxially to whose interior is a rotor 3, the secondary. In the stator 2 is provided one or more pair of polar expansions, two in the example shown, indicated as C_1 and C_2 . The polar expansions E_1, E_2, E_3, E_4 and the pair C_1 with C_2 are mutually separated by a polar step (p), i.e. the distance measured on the air gap arc between the start of a permanent magnet and its centre (half magnet). Each polar expansion (E_1, E_2, E_3, E_4) is provided with a horseshoe shaped ferromagnetic core (A_1, A_2, A_3, A_4), and with electromagnetic coils ($B_1, B_1', B_2, B_2', B_3, B_3', B_4, B_4'$). In the secondary, the rotor 3 is provided with a succession of alternate heteronomous permanent magnets $3_1, 3_2, \dots, 3_{10}$, separated from the polar expansions E_1, E_2, E_3, E_4 by an air gap 4. Further provided is a system for controlling the motor, of a known kind, schematically illustrated in the brush collector 5, characterised by neutral polar steps (p_2) and conductor polar steps (p_1) for the alternating electrical switching of the coils (B_1, B_1', B_2, B_2') or (B_3, B_3', B_4, B_4'), with polarity inversion due to the negative

feedback with the heteronomous alternate permanent magnets on the output polar step of each half magnet.

In other words, the machine comprises one or more pairs C_1, C_2 of polar expansions, E_1 and E_3, E_2 and E_4 , mechanically and electrically distanced by a polar step (p) equal to a fourth of a cycle and "half a permanent magnet" 3 whereof one expansion, E_1 and E_3 , positioned opposing the full position of the alternated heteronomous permanent magnets 3_2 and $3_3, 3_7$ and 3_8 , and the other, E_2 and E_4 , astride the permanent magnets, $3_4, 3_5$ and $3_6, 3_9, 3_{10}$ and 3_{11} , obtaining as a result a balanced equilibrium of the ferromagnetic torque forces interacting between the high permeability cores, A_1 and A_2, A_3 and A_4 , with the alternated heteronomous permanent magnets, $3_1, 3_2, \dots, 3_{10}$, and an electrical offset between the electromagnetic coils of the pair B_1, B_1' and B_2, B_2', B_3, B_3' and B_4, B_4' , for the contiguous closure of the alternate steps superposed in the two complete and separate cycles of positive and negative energy on two heteronomous permanent magnets of opposite polarity in four fourths of a cycle (12, 14, 13 and 15; 16, 18, 19 and 17), each electromagnetic coil of the pair or group of coils equally positioned in phase (B_1, B_1', B_3 and $B_3'; B_2, B_2', B_4$ and B_4') alternatively act for two separate fourths of a cycle with "artificial electromagnetic or mechanical energy" (12 and 13; 14 and 15) during the conductor steps (p_1) and for two separate fourths of a cycle with "natural ferromagnetic energy" (16 and 17; 18 and 19) during the neutral steps (p_2) electrically isolated, through the related control system 5, completing the two cycles of separate, consecutive, superposed and parallel "artificial" energy 12, 14, 13 and 15 plus the "natural" energy 16, 18, 19 and 17. When the dynamo-electric machine operates as a generator of mechanical energy, i.e. as a motor, each electromagnetic coil or group of coils (B_1, B_1', B_3 and $B_3'; B_2, B_2', B_4$ and B_4') equally positioned are powered with positive and negative electrical current to obtain the negative feedback from the centre of the permanent magnets for the polar step (p_1) until the end of the permanent magnets at alternating steps 12, 14, 13 and 15 and contiguous for a complete repulsion cycle on two magnets of opposite polarity and for two separate fourths each

(12 and 14; 13 and 15) whilst the "natural" cycle of permanent magnetic attraction is conducted by the ferromagnetic cores ($A_1, A_3; A_2, A_4$) in parallel and superimposed to the "artificial" cycle during the neutral polar steps (p_2) of the non-powered coils (16, 18, 19 and 17) also for two separate two fourths each (16 and 17; 18 and 19); vice versa when the dynamo-electric machine operates as a generator of electrical energy it is powered with mechanical energy aided by the complete cycle of "natural" magnetic attraction during the neutral steps (p_2).

The illustrated embodiment of a polar expansion is related to an ideal circuit with the closure of the electromagnetic flow in a pair of successive permanent magnets with opposite polarity.

Hereafter, the description shall show how a dynamo-electric machine thus realised presents a harmonisation of the interacting forces and, as a consequence, a high efficiency.

For the sake of simplicity hereafter the case shall be considered of polar expansions not interacting with pairs of permanent magnets but with one permanent magnet at a time.

In particular, in the case wherein the machine operates as a motor, in Figure 2 the indications A_1 and B_1 denote respectively a ferromagnetic core and an electromagnetic coil of a polar expansion E_1 of the primary, and the indication 3_1 denotes a permanent magnet of the secondary. For the sake of convenience, the relative motion of the polar expansion of A_1, B_1 , with respect to the permanent magnet 3_1 is considered, as if the rotor were fixed.

The ferromagnetic core of A_1 has high permeability so that it is attracted towards the permanent magnet 3_1 , by the "natural" ferromagnetic attraction when the coil B_1 is not energised. The polar expansion E_1 moves to E_1' . The corresponding energy is proportional to the surface area of the right triangle 6. The "artificial" electromagnetic repulsion when the coil B_1 is energised is proportional to the surface area of the triangle 7. The polar expansion E_1 moves to E_1'' .

With reference to Figure 3, a complete attraction and repulsion with alternating

steps of a polar expansion E_1 , with a pair of heteronomous permanent magnets 3_1 and 3_2 of opposite polarity, is shown schematically. The polar expansion E_1 moves to E_1' by "natural" magnetic attraction between said permanent magnet 3_1 and the ferromagnetic core A_1 . The corresponding energy is proportional to the surface area of the rectangle 8. The "artificial" electromagnetic repulsion when the coil B_1 is energised with positive electrical power proportional to the surface area of the rectangle 9. The polar expansion E_1 moves to E_1'' . Hence, by "natural" magnetic attraction with the permanent magnet 3_2 , the polar expansion E_1 moves to E_1''' . The corresponding energy due to "natural" permanent magnetic attraction is proportional to the surface area of the rectangle 10. Thus, the "artificial" electromagnetic repulsion when the coil B_1 is energised with negative electrical power, proportional to the surface area of the rectangle 11, takes the polar expansion E_1 to E_1'''' , ready in attraction for another cycle. With reference to Figure 4, the mechanical coupling (C) distancing the ferromagnetic cores A_1 and A_2 for the balance of the "natural" permanent magnetic attraction forces between a permanent magnet and the other ($3_1, 3_2, 3_3, 3_4, \dots$) said ferromagnetic cores (A_1 and A_2) are distanced by a magnetic step p equal to half a permanent magnet, as in the motor shown by way of example in Fig. 1, or half permanent magnet plus one as in the scheme of the aforementioned example of a complete cycle Fig. 4, or half a permanent magnet plus a plurality of whole permanent magnets equally distanced ($\frac{1}{2}, 1\frac{1}{2}, 2\frac{1}{2}, \dots$). Thus the "natural" ferromagnetic attraction torque forces are balanced and cancel each other out; moreover, the phase offset (p) between the coils (B_1 and B_2) by half permanent magnet has the purpose of completing with continuity the two parallel separate and superposed energy cycles over all the four steps necessary for the "natural" permanent attraction energy and to the "artificial" electromagnetic repulsion energy. Also schematically shown is the attraction cycle between the ferromagnetic cores A_1 and A_2 and the complete repulsion cycle of a pair of polar expansions E_1 and E_2 with the respective alternated heteronomous permanent magnets ($3_1, 3_2, 3_3, 3_4$) for each polar expansion E_1 and E_2 and each ferromagnetic core A_1 and A_2 one can repeat what has

been stated with reference to Figure 3, stressing again that, thanks to the half-magnet polar step (p), a harmonisation is reached between the "natural" magnetic forces and "artificial" electromagnetic forces, which leads to an increase in efficiency with respect to the case wherein power supply to the coils is continuous in the positive and respectively in the negative semi-cycle. The positive and negative electrical power supply cycle for the two coils of E_1 and E_2 is instead that of Figure 5, detailed in 12, 13, 14 and 15 for four steps of a complete cycle. Figure 6 instead shows the action of the ferromagnetic attraction forces in the same cycle steps 16, 17, 18, 19.

Therefore, when the dynamo-electric machine operates as a motor, each electromagnetic coil is powered with positive and negative electrical current or vice versa only for two separate fourths of cycle during a complete attraction and repulsion cycle on two successive heteronomous magnets.

To summarise, the dynamo-electric machine according to the invention has in its primary at least a pair of polar expansions, whereof one positioned opposing the centre of a permanent magnet of a series of alternated heteronomous permanent magnets of the secondary, and the other expansion positioned opposing astride two of said permanent magnets. The pair of polar expansions has a function of balancing and completing the fractioned cycle of linear electrical power supply at contiguous segments as well as the "natural" fractioned cycle separately (the coils of the expansions work only in repulsion on the output of half the permanent magnets; the highly permeable ferromagnetic cores work only in attraction on the input of half the permanent magnets).

In other words, the power supply of the polar expansions at alternating steps occurs when the ferromagnetic core is at the centre of a permanent magnet in negative feedback until the end of the permanent magnet, whilst in natural ferromagnetic attraction from the start of the permanent magnet to its centre, first one then the other linearly uniting the fractioned force cycle. The energy developed in the electrical power supply cycle and the one developed in the natural permanent magnetic cycle are added in interacting forces at the axis of the machine. The alternated power direct

current power supply of the polar expansions and of at least one pair, first one and then the other expansion in negative feedback (repulsion) occurs at complete cycles and with continuous absorption and the "artificial" electrical energy is transformed into mechanical energy, whilst the attraction at alternating steps between the ferromagnetic cores of at least one pair and the permanent magnets at the input first one and then the other core, create a further "natural" mechanical energy superimposed and parallel, continuous and linear which is added at the axis with the transformed "artificial" energy. Vice versa, if the dynamo-electric machine of the present invention operates as a generator of mechanical energy the axis of the machine is powered with mechanical energy which is transformed into electrical current by each electro-magnetic coil for two separate fourths of cycle each during a complete cycle, the energy produced is drawn by means of the control system during the conductor steps, whilst the "natural energy" of the neutral steps active in attraction add their energy to the mechanical one provided to the axis, with the result of a dual transformed energy and with total power relating to the sum of each separate cycle; or with the separate and direct withdrawal from the equally positioned coils belonging to the two superimposed energy cycles, in this case their electrical energy can be rectified before rejoining at the output, or re-phased.

The harmonisation of the aforementioned interacting forces characterises the "energy generator" invention as a high efficiency dynamo-electric machine.

With reference to Figure 7, a schematic representation is provided of a first possible form of interaction of a polar expansion with closure of the magnetic flow and with a pair of heteronomous permanent magnets $3_1, 3_2$ in opposite position with the ferromagnetic core (A_1'), as in the example of Figure 1, for rotatory and linear dynamo-electric machine, said polar expansion can be position both linear circular and longitudinally to the axis of the secondary with alternated heteronomous permanent magnets, in this case with double band.

With reference to Figure 8 the polar expansion E" has air gaps at both sides of a ferromagnetic core (A_1'') in axial disposition with respect to the band of the alternated

heteronomous permanent magnets for the closure of the magnetic flow 20, as in the case of a so-called linear and linear annular motor.

With reference to Figure 9, the polar expansion E" ' for the closure of the magnetic flow has permanent magnets at both sides of the ferromagnetic core (A₁" ') with two bands of alternated heteronomous permanent magnets 21, 22 belonging to two axial rotors or two linear tracks. Moreover, without references, it should be noted that for the construction and disposition of the polar expansions, of the ferromagnetic cores, of the permanent magnets and of its air gaps the realisation can be effected as in common and known dynamo-electric machines, it is just necessary according to the invention to respect the binomial of separation of the interacting flows to be harmonised with the alternating "artificial" electrical power supply of the active steps and of the neutral steps (not powered), which allow to exploit the "natural" potential attraction energy between the ferromagnetic cores and the permanent magnets always unbalanced in magnetic attraction step after step, main and necessary characteristic of the subject invention.

Purely by way of experimental, demonstrative, theoretical and practical example, the invention can be realised with two dynamo-electric machines with collector, appropriately and simply modified for the exploitation of the technique for separating the interacting forces constituting the subject of the invention: the two collectors are modified, each electrical polar step is divided into two steps, a neutral one and a conductor one, the axes of the two machines are fixed mechanically in series, forming a common mechanical axis, taking into account that it is necessary to offset by a polar step a collector of a machine with respect to the other one of the other machine, so that for instance in the case of a motor the electrical power supply powers at alternating polar steps first one machine and then the other, transforming the electrical energy from "artificial" repulsive electromagnetic force into mechanical energy, whilst the natural magnetic potential energy of the neutral polar steps in ferromagnetic attraction creates an additional "natural" mechanical energy parallel and superimposed with a resultant at the axis given by the sum of the energies at play,

1870
 1871
 1872
 1873
 1874
 1875
 1876
 1877
 1878
 1879
 1880
 1881
 1882
 1883
 1884
 1885
 1886
 1887
 1888
 1889
 1890
 1891
 1892
 1893
 1894
 1895
 1896
 1897
 1898
 1899
 1900
 1901
 1902
 1903
 1904
 1905
 1906
 1907
 1908
 1909
 1910
 1911
 1912
 1913
 1914
 1915
 1916
 1917
 1918
 1919
 1920
 1921
 1922
 1923
 1924
 1925
 1926
 1927
 1928
 1929
 1930
 1931
 1932
 1933
 1934
 1935
 1936
 1937
 1938
 1939
 1940
 1941
 1942
 1943
 1944
 1945
 1946
 1947
 1948
 1949
 1950
 1951
 1952
 1953
 1954
 1955
 1956
 1957
 1958
 1959
 1960
 1961
 1962
 1963
 1964
 1965
 1966
 1967
 1968
 1969
 1970
 1971
 1972
 1973
 1974
 1975
 1976
 1977
 1978
 1979
 1980
 1981
 1982
 1983
 1984
 1985
 1986
 1987
 1988
 1989
 1990
 1991
 1992
 1993
 1994
 1995
 1996
 1997
 1998
 1999
 2000
 2001
 2002
 2003
 2004
 2005
 2006
 2007
 2008
 2009
 2010
 2011
 2012
 2013
 2014
 2015
 2016
 2017
 2018
 2019
 2020
 2021
 2022
 2023
 2024
 2025
 2026
 2027
 2028
 2029
 2030
 2031
 2032
 2033
 2034
 2035
 2036
 2037
 2038
 2039
 2040
 2041
 2042
 2043
 2044
 2045
 2046
 2047
 2048
 2049
 2050
 2051
 2052
 2053
 2054
 2055
 2056
 2057
 2058
 2059
 2060
 2061
 2062
 2063
 2064
 2065
 2066
 2067
 2068
 2069
 2070
 2071
 2072
 2073
 2074
 2075
 2076
 2077
 2078
 2079
 2080
 2081
 2082
 2083
 2084
 2085
 2086
 2087
 2088
 2089
 2090
 2091
 2092
 2093
 2094
 2095
 2096
 2097
 2098
 2099
 2100
 2101
 2102
 2103
 2104
 2105
 2106
 2107
 2108
 2109
 2110
 2111
 2112
 2113
 2114
 2115
 2116
 2117
 2118
 2119
 2120
 2121
 2122
 2123
 2124
 2125
 2126
 2127
 2128
 2129
 2130
 2131
 2132
 2133
 2134
 2135
 2136
 2137
 2138
 2139
 2140
 2141
 2142
 2143
 2144
 2145
 2146
 2147
 2148
 2149
 2150
 2151
 2152
 2153
 2154
 2155
 2156
 2157
 2158
 2159
 2160
 2161
 2162
 2163
 2164
 2165
 2166
 2167
 2168
 2169
 2170
 2171
 2172
 2173
 2174
 2175
 2176
 2177
 2178
 2179
 2180
 2181
 2182
 2183
 2184
 2185
 2186
 2187
 2188
 2189
 2190
 2191
 2192
 2193
 2194
 2195
 2196
 2197
 2198
 2199
 2200
 2201
 2202
 2203
 2204
 2205
 2206
 2207
 2208
 2209
 2210
 2211
 2212
 2213
 2214
 2215
 2216
 2217
 2218
 2219
 2220
 2221
 2222
 2223
 2224
 2225
 2226
 2227
 2228
 2229
 2230
 2231
 2232
 2233
 2234
 2235
 2236
 2237
 2238
 2239
 2240
 2241
 2242
 2243
 2244
 2245
 2246
 2247
 2248
 2249
 2250
 2251
 2252
 2253
 2254
 2255
 2256
 2257
 2258
 2259
 2260
 2261
 2262
 2263
 2264
 2265
 2266
 2267
 2268
 2269
 2270
 2271
 2272
 2273
 2274
 2275
 2276
 2277
 2278
 2279
 2280
 2281
 2282
 2283
 2284
 2285
 2286
 2287
 2288
 2289
 2290
 2291
 2292
 2293
 2294
 2295
 2296
 2297
 2298
 2299
 2300
 2301
 2302
 2303
 2304
 2305
 2306
 2307
 2308
 2309
 2310
 2311
 2312
 2313
 2314
 2315
 2316
 2317
 2318
 2319
 2320
 2321
 2322
 2323
 2324